

Firmware update

Before starting to commission the KNX panel (see application description KNX panel 7"), ensure that the KNX panel's firmware is up to date.

You can upload the firmware onto your KNX panel in two ways:

Online

The easiest way to update the KNX panel online is to connect it to the Internet via LAN.

- > Boot up the KNX panel.
- > Tap the settings icon.
- > Log in as Manager (**Login** – PIN code when delivered **7415369**).
- > Tap **Panel preference** in the menu. The screen with the settings is displayed.^{*)}
- > Tap **Maintenance** and in the next screen **System Update**.
- > Tap **CHECK ONLINE FOR UPDATES** SUCHEN.
- > If an update is found on the server, a corresponding message is shown.
Confirm with **OK**.
- > The update is loaded and installed. This can take a few minutes.
The KNY panel is then rebooted.
- > Take the KNX panel into operation (see application description KNX panel 7").

Offline

If the KNY panel is not connected to the Internet, you can install the update on the KNX panel using a USB stick. To do this, however, you require access to the USB port on the rear of the panel.

- > Download the firmware update bundle with a PC from the Feller homepage www.feller.ch
- > Unpack the bundle and save the firmware update **.zip** and the signature file **.asc** on a USB stick.
- > Boot up the KNX panel.
- > Tap the Settings icon.
- > Log in as Manager (**Login** – PIN code when delivered **7415369**).
- > Tap **Panel Einstellungen** in the menu. The screen with the settings is displayed.^{*)}
- > Tap **Maintenance** and in the next screen **System Update**.
- > Plug the USB stick into the USB port on the rear of the panel and tap the corresponding **BROWSE USB DISK #x**.
- > Select the corresponding **.zip** file.
- > Tap **UPDATE USING THE SPECIFIED 'UPDATE.ZIP' FILE**.
- > The update is loaded and installed. This can take a few minutes.
The KNY panel is then rebooted.
- > Remove the USB stick.
- > Take the KNX panel into operation (see application description KNX panel 7").

^{*)} If the user interface of the panel settings are still in German, this can be changed to German with **Allgemein – Sprache auswählen**. With ◀ you can go back one screen and with ○ you can return to the user interface of the KNX panel.



Attention

After the firmware update, the old PIN is no longer valid. The new PIN is then **74269** (see current application description KNX panel 7").